



S11???????? 30-2500kVA 10/0.4kV ?????? ????

???? :

??	????
???	??
?????	10
????	OEM?ODM?OBM
????	1000
????	???

???? :

????????

????????????????????????????????????????????????????????????45°????????????????????????????????????????????
 ?????????????????????????????????????????????????????????????
 ?????????????????????????????????????????????????????????????????????????????????????????????????????
 ??????A??B????????????????????????????????????????????????????????????????????????????????????????
 500kVA????????????????????????????????????????????????????????????
 ??????????????GB/T 6451??????????

???? (kVA)	?? (kV)	????	?? (kV)	?????	???? (kW)	???? (kW) 75?	???? (%)	???? (%)
30	10	±5%?±2×2.5%	0.4	Yyn0 / Dyn11	0.10	0.63 / 0.60	1.50	4.0
50	10	—	0.4	—	0.13	0.91 / 0.87	1.30	4.0
100	10	—	0.4	—	0.20	1.58 / 1.50	1.10	4.0
200	10	—	0.4	—	0.34	2.73 / 2.60	1.00	4.0
400	10	—	0.4	—	0.57	4.52 / 4.30	0.80	4.0
630	10	—	0.4	—	0.81	6.20	0.60	4.5

