



???? (kVA)	???? (kW)	???? (kW) 75?	???? (%)	???? (%)
800	0.785	8.93	0.52	6.5
1000	0.920	10.9	0.52	6.5
1250	1.12	13.2	0.48	6.5
1600	1.35	15.8	0.48	6.5
2000	1.59	19.7	0.44	6.5
2500	1.89	23.2	0.44	6.5

??500kVA?????????Dyn11?????????Yyn0?????????630kVA???Dyn11????
 ??????????-25??+40?????1000m????????????????????????????????????
????
35kV??0.4kV????????????10kV????????????????????????10kV???????
 ?????????????????????????GB 20052????????S11????????15%-
 20%????????????????????????
 ???
 ?????????????????????????0.44%~1.0%????????????
 ?????????????????????????????????35kV????????
 ?????????????????Yyn0?Dyn11?Dyn11????????????????
????
35kV????????????????????35kV????????0.4kV????????
 ?????????????????????35kV????????????/????
 ?????????????????????????35kV/0.4kV??
 ?????????????????????????????????
 ?????????????????????????10kV????????35kV????????
 ?????????????????????????35kV????????????
????????
 ???S13 35kV????????????????????35kV????????????
 ?????????????????23QG085?27QG090????????????????
 ?????????????????????????????
 ?????????????????????????????????
 ?????????????????±5%?±2x2.5%????????Yyn0?Dyn11????????6.5%?8%????????IP????????
 ?????????????????????????????
 ?????????35kV????????????????????